




AC1200


Dual Band Wi-Fi

Range Extender

- 

1200Mbps Wi-Fi Dual Band
- 

One click Fast Pairing
- 

Smart LED Indicators
- 

External Dual-Band antennas

Wi-Fi 5

Extend your Wi-Fi

Anytime, Anywhere



Plug&Play

Exigo Hub M20-E does not require reconfig-uration on the relocation of the device



High-Speed Dual Band Wi-Fi

Supports 802.11 ac technology with backward compatibility
Delivers faster speed of Dual-band Wi-Fi up to 1167 Mbps
Live streaming of HD videos and play games online



Simultaneous Dual-Band

Operates at 2.4 GHz and 5GHz to extend Wi-Fi coverage
Reduce Wi-Fi dead spots



One-Click Fast pairing

Easy configuration by simply pressing the WPS button on both Exigo Hub M20-E and your wireless router to extend the coverage of your existing WLAN network



Stable Wi-Fi with Two External 5dBi Antennas

Two external dual-band high-performance antennas with MIMO technology for stable performance.

Product Introduction

Exigo Hub M20-E Dual-band Wi-Fi range extender is a convenient wall-plug design with two external high-performance Omni-directional antennas. The device has MIMO technology to ensure a stable wireless connection and data transmission for multiple Wi-Fi devices with optimal performance. The Exigo Hub M20-E supports IEEE 802.11 b/g/n 2.4GHz and IEEE 802.11 a/n/ac 5GHz standards.

The Exigo Hub M20-E offers a 100Mbps Fast Ethernet port which enables ethernet connection to devices such as Laptops, Gaming Consoles, and Smart Speakers.

The extender is compatible with any wireless router gateway, or cable/ADSL modem supporting Wi-Fi.

Features

- Complies with 802.11ac/a/b/g/n standards.
- Turns your single band Wi-Fi to dual band Wi-Fi.
- Delivers up to 300Mbps on 2.4G band or 867Mbps on 5G band.
- Two external antennas enhance the throughput's stability.
- Supports easy and quick setup by smart phones.
- Supports WPS (Wi-Fi Protected Setup) with one-click button.
- Two signal strength LED indicators help you get optimum position for extender.
- Supports two working modes: AP Mode and Extender Mode.
- Wall-plug design saves your space.

Interface

- 1 *10/100Mbps Ethernet port

Power Supply

- AC 100V~240V / 50~60Hz 0.1A

Buttons

- 1 *5GHz WPS
- 1*2.4GHz WPS
- 1*RST

LED Indicators

- 1 *Power
- 1 *CPU
- 1 *5G EXT
- 1*2.4G EXT
- 1*LAN

Antennas

- 2 *5dBi fixed dual band antennas

Dimensions

- 117 x 72 x 66mm (without antennas)

Standards

- IEEE 802.11ac
- IEEE 802.11n
- IEEE 802.11g
- IEEE 802.11b
- IEEE 802.11a

RF Frequency

- 2.4GHz/5GHz

Data rate

- 2.4GHz: 300Mbps
- 5GHz: 867Mbps

EIRP

- 2.4GHz < 20dBm
- 5GHz < 20dBm

Reception Sensitivity

- 2.4GHz:
 - 11b 11M: -81dBm @ 8%PER
 - 11g 54M: -68dBm @ 10%PER
 - 11n HT20 MCS7: -65dBm @ 10%PER
 - 11n HT40 MCS7: -62dBm @ 10%PER
- 5GHz:
 - 11a 54M: -68dBm @ 10%PER
 - 11n HT20 MCS7: -65dBm @ 10%PER
 - 11n HT40 MCS7: -62dBm @ 10%PER
 - 11ac VHT80 MCS9: -51dBm @ 10%PER

Advanced Features

- Easy Wi-Fi Extension by Smart Phone

Device images



Giftbox



Package Includes

- Exigo Hub M20-E
- Quick Start Guide

Device Identification

Device name: Exigo Hub M20-E

SKU: EX-NN-D2-MT-123

Part Number: EX-M20-1G-DB2-EM

Barcode: 0754590921800

Serial Number: 0101220085XXXXXX

User Manual



Xunison

Bracken Business Park, Bracken Rd, Sandyford Business Park, Sandyford, Dublin, Ireland

www.xunison.com