



Xunison Hub M20-E



AC1200

Dual Band Wi-Fi Range Extender

- Speeds up to 1200 Mbps
- Rapid one-button pairing
- External Dual-Band antennas
- Plug and play configuration

Extend your Wi-Fi

Anytime, Anywhere

Product Introduction

Xunison Hub M20-E Dual-band Wi-Fi range extender is a convenient wall-plug design with two external high-performance Omni-directional antennas. The Xunison Hub M20-E over a 100Mbps Fast Ethernet port which enables ethernet connection to devices such as Laptops, Gaming Consoles, and Smart Speakers. The extender is compatible with any wireless router gateway, or cable/ADSL modem supporting Wi-Fi.



Plug & Play

Xunison Hub M20-E does not require reconfiguration on the relocation of the device



Stable Wi-Fi with Two External 5dBi Antennas

Two external dual-band high-performance antennas with MIMO technology for stable performance.



High-Speed Dual Band Wi-Fi

Supports 802.11 ac technology with backward compatibility and Wi-Fi speed up to 1167 Mbps, supports live streaming of videos.



Simultaneous Dual-Band

Operates at 2.4 GHz and 5GHz to extend Wi-Fi coverage, reduce Wi-Fi dead spots



One-Click Fast pairing

Easy configuration by simply pressing the WPS button on both Xunison Hub M20-E and your wireless router to extend the coverage of your existing WLAN network



Bracken Business Park, Bracken Rd, Sandyford Business Park, Sandyford, Dublin, Ireland

www.xunison.com



Xunison Hub M20-E

SPECIFICATIONS

Data Range	2.4GHz: 300 Mbps
	5 GHz: 867 Mbps

Features	Turns your single band Wi-Fi to dual band Wi-Fi.
	Two external antennas enhance the throughput's stability.
	Supports easy and quick setup by smart phones.
	Supports WPS (Wi-Fi Protected Setup) with one-click button.
	Two signal strength LED indicators help you get optimum position for extender.
	Wall-plug design saves your space

Wireless Standards	802.11 ac/a/b/g/n standards.
--------------------	------------------------------

Wi-Fi Antennas	2 *5dBi fixed dual band antennas
----------------	----------------------------------

EIRP	2.4GHz < 20 dBm
	5 GHz < 20 dBm

Operation Mode	AP
	Extender

Reception Sensitivity	2.4 GHz 11b 11M : -81dBm @ 8%PER 11g 54M : -68dBm @ 10%PER 11n HT20 MCS7 : -65dBm @ 10%PER 11n HT40 MCS7 : -62dBm @ 10%PER
	5 GHz 11a 54M : -68dBm @ 10%PER 11n HT20 MCS7 : -65dBm @ 10%PER 11n HT40 MCS7 : -62dBm @ 10%PER 11ac VHT80 MCS9 : -51dBm @ 10%PER



Bracken Business Park, Bracken Rd, Sandyford Business
Park, Sandyford, Dublin, Ireland

www.xunison.com



Xunison Hub M20-E

Physical Interface	1 *10/100Mbps Ethernet port
Buttons	1*5GHz WPS
	1*2.4GHz WPS
	1*RST
LED Indicators	Power indicator
	CPU indicator
	5G EXT indicator
	2.4G EXT indicator
	LAN indicator
Advanced Features	Easy Wi-Fi Extension by Smart Phone
Dimensions	117 x 72 x 66mm (without antennas)
Power Supply	AC 100V~240V / 50~60Hz 0.1A
Package Includes	Xunison Hub M20-E
	Quick Start Guide



Bracken Business Park, Bracken Rd, Sandyford Business
Park, Sandyford, Dublin, Ireland

www.xunison.com

DEVICE IMAGES



DEVICE IDENTIFICATION

Brand	Xunison
Device name	Xunison Hub M20-E
SKU:	EX-NN-D2-MT-123
Part Number	EX-M20-1G-DB2-EM
Barcode	0754590921800
Serial Number	0101220085XXXXXX